


## Proximity Reader

Proximity access control allows registered staffs and parents to gain entry automatically after being verified by the reader next to the entrance. This saves staffs' time considerably from the repetitive work of opening door to parents and other members of staff every day. It also comes with a complete user access logs.




### Key Features:

- 125KHz Proximity Card Reader
- Register up to 500 users
- Read Range: Up to 4 inch (10cm)
- Dual Reading Technology (Active and Passive Cards)
- External LED Control
- External Buzzer Control
- Indoor / Outdoor Operation
- 26bit Wiegand (default) / RS232 and ABA Track II (optional) Output Format Easy to install on Metal Door Frame or Mullion
- Solid Epoxy Potted
- Waterproof / IP65 / IP66
- Reverse Polarity Protection

### Specifications:

Read Range/ Time	Up to 10cm/ 30ms
Power	DC5 - 12V/ Max. 180mA (@DC 12V RS232 Output)
Output Format	26 bit Wiegand, RS232 & ABA Track II Magnetic Stripe (optional)
External Buzzer Control Input	Max. 50mA; Low Active, DC 0 - 5V
External LED Control Input	Max. 50mA; Low Active, DC 0 - 5V
LED/ Buzzer	2 Colour LED (red & green)/ Piezo Buzzer
Operation Environment	-35°C ~ 35°C
Operation Humidity	0 ~ 90%
Colour	Dark Pearl Grey
Dimension (W x H x D)	46mm x 122mm x 23mm
Weight	160g

\* Specifications are subject to change without notice



NurseryCam 